



Battery Capacity Tester

AC milliohmmeter checks Battery Condition in seconds

While the battery is in service

Features:

- · On-line testing without disconnecting battery
- Built-in datalogger manually stores up to 999 sets and 9600 sets for continuous datalogging
- · Simultaneously measures DC Voltage and AC Milliohms
- · Auto power off
- Includes Windows® 95/98/NT/2000/ME/XP compatible software for downloading readings to a PC





Specifications	Range	Resolution	Basic Accuracy
Resistance	40mΩ, 400mΩ,	10μΩ, 100μΩ,	\pm (1% reading \pm 10d)
	4Ω , 40Ω	1m $Ω$, 10 m $Ω$	
Voltage	4V, 40V	1mV, 10mV	\pm (0.1% reading \pm 6d)
Max Input Voltage	50VDC		
Manual Datalogging	999 sets		
Continuous Datalogging	9600 sets		
Power	6 AA batteries		
Battery life	7 hours		
Dimensions	9.75 x 4 x 1.75" (250 x 100 x 45 mm)		
Weight	17.5oz (500g)		

Ordering Information:

BT100Battery Capacity Tester **BT102**120V AC Adaptor

BT100-ALReplacement Alligator Clips for BT100 **BT100-TL**Replacement Test Leads for BT100

USB100RS-232 to USB Adaptor